
VZ-R Firmware Update



Please also note that you'll need a computer running Windows or Mac OS in order to perform this update.



2 Make sure that the VZ-R is **turned off**.





4 Make sure that the VZ-R is **set to 6ohz**.

5 Press and hold the filter button.

6 While pressing the filter button, turn on the VZ-R and hold until an external drive appears. On a Mac, the drive will most likely appear on your Desktop as 'No Name'. In Windows, it will appear as an external drive.

Copy the ApproSysFW.bin file into the drive. In most cases, you can simply drag the .bin file and drop it in.











8 After the copy is complete, please eject the drive. On a Mac, you can simply drag the drive into the Trash. In Windows, you can right-click and eject.

9 Turn off the VZ-R.

10 Turn the VZ-R back on and the white LED will flash multiple times. This process will take about 1 minute to complete.

¹¹After the white LED stops flashing, you may open Visualizer and confirm that the VZ-R's firmware has been updated to version 2014. You can find the FW version in the Select Camera drop-down list.



